

16 CHANNEL BUS LINE TRANSMITTER - 81710000

IMPORTANT

The Busline Transmitter needs to have a Base ID set to make it recognisable to the Control System, please ensure that Blindware is notified of Base ID numbers to be set at time of ordering.

Programming Motolux Tubular Motors to the 16 Channel Busline Transmitter

Please ensure that the DC Adapter is plugged in and the unit is powered on beforehand.

Using a Motolux Multi-Channel Remote Control:

Pair and set the limits for each motor using the specific instructions for each different type of Motolux Tubular Motor being used.

- On the Remote Control:** Using the Channel Buttons, scroll across to the channel that you would like to add to the Busline Transmitter.
- On the Busline Transmitter:** using the up and down Channel Buttons scroll across to the channel that you would like the motor to be added to.
- On the Remote Control:** Push and Hold the **STOP Button** until the blind jiggles.
On the Busline Transmitter: Push and Hold the **UP Button** on the top panel of the Busline Transmitter, the blind will jiggle. This Blind has now been copied across to the Busline Transmitter. Test the operation.
To copy more channels across to the Busline Transmitter: Repeat the above steps for each consecutive channel.

Programming Motolux Curtain Motors to the 16 Channel Busline Transmitter

- Using a Motolux Multi-Channel Remote Control:** Pair and set the limits for each motor using the specific instructions for each different type of Motolux Curtain Motor being used.
- On the Remote Control:** Using the Channel Buttons, scroll across to the channel that you would like to add to the Busline Transmitter.
On the Busline Transmitter: using the up and down channel buttons scroll across to the channel that you would like the motor to be added to.
- On the Remote Control:** Push and Hold the **STOP Button** until the Red Light on the bottom of the Curtain Motor starts flashing.
On the Busline Transmitter: Push and Hold the **UP Button** on the top panel of the Busline Transmitter, the light on the bottom of the Curtain Motor will give Three Blue flashes. This Curtain Motor has now been copied across to the Busline Transmitter. Test the operation.
To copy more channels across to the Busline Transmitter: Repeat the above steps for each consecutive channel.

